



## CHINT Smart Power Sensor For HUAWEI EV-Charger Solution

### ACCURACY

Measurement accuracy better than class 1 within full temperature range

### SIMPLE & EASY

- › Standard din-rail mounting of DIN 35 mm
- › Small volume, Width: 72mm
- › LCD display, convenient for users to set and check
- › Visual color identification with simple wiring

### GREEN

- › Overall power consumption  $\leq 2$  W

## CHINT Smart Power Sensor For HUAWEI EV-Charger Solution



### Technical Specification

### DSU666-FE

Mechanical Parameter	
Dimension (W×D×H)	72×98×65.5 mm
Mounted Type	DIN35 Rail
Power supply	
Power Grid Type	3P4W
Input Voltage	85VAC~288VAC (phase voltage)
Power Consumption	≤2W
Auxiliary Power Supply	85VAC~288VAC (L,N)
Measurement Range	
Line Voltage	147VAC~499VAC
Phase Voltage	85VAC~288VAC
Current	0A ~100A
Measurement Accuracy	
Voltage	±0.5%
Current	±1%
Frequency	±0.01Hz
Power	±1%
Energy	±1%
Communication	
Interface	1-Way Ethernet
Communication Protocol	Modbus-TCP
Environment	
Operating Temperature	-25°~ 60°
Storage Temperature	-40°C ~ 70°C
Operating Humidity	5% ~ 95% (non-condensing)
Other	
Attachment	Current Transformer



Copyright© CHINT GLOBAL PTE. LTD.2022. All rights reserved.

No part of this document may be reproduced or transmitted in any form or by any means without prior written consent of CHINT GLOBAL PTE. LTD

#### General Disclaimer

The information in this document may contain predictive statements including, without limitation, statements regarding the future financial and operating results, future product portfolio, new technology, etc. There are a number of factors that could cause actual results and developments to differ materially from those expressed or implied in the predictive statements. Therefore, such information is provided for reference purpose only and constitutes neither an offer nor an acceptance. CHINT may change the information at any time without notice.

For orders and information, please contact [hongys@chintglobal.com](mailto:hongys@chintglobal.com)

#### CHINT ITALIA INVESTMENT SRL

Add: Via Bruno Maderna 7  
30174 Venezia (Italia)  
Tel: +39 3896692658  
E-mail: [hongys@chintglobal.com](mailto:hongys@chintglobal.com)

#### CHINT ELECTRICS S.L.

Add: Calle José Echegaray, Num 8.Parque  
Empresarial Las Rozas Edificio 3, Planta Baja,  
Oficina 7-8.C.P: 28232 Las Rozas (Madrid)  
Tel: +34 91 645 03 53  
E-mail: [hongys@chintglobal.com](mailto:hongys@chintglobal.com)

